



MOTION 868 MHz range

Applicable to doors
roller · folding · sliding · swing · sectional
guillotine · revolving · posts

GOPRO

programmable radio transmitter



jcmtechnologies
be a step ahead with technology and imagination

PRO transmitters offer all of the advantages of the JCM transmitters with the added value of programming to provide absolute domain over the registering of new receivers. Characteristics such as the APS, rolling security code and remote control management via PC offer great added value to this group of transmitters.



GOPRO MINI · GOPRO2 · GOPRO4
MUVPRO2 · MUVPRO4



Great reliability and feeling of higher range for users

- With the APS (Approaching System) transmission system, the transmitter button can be pressed even outside the receiver range. The transmitter will repeatedly send the signal while the user approaches his garage door and until the door opens.

- 1 The user activates the transmitter outside the range.



Within 15 seconds he/she enters the range. The door remains closed.



- 3 The receiver receives the signal automatically without re-activating the transmitter and opens the door.



Great security

- High security rolling code system with more keying bits.

Installer personalisation

- The installer can personalise the transmitter using the installer code and ASSISTANT and PROG-MAN programming tools.

Flexibility and speed when programming equipment

- The transmitters and proximity equipment are programmed by radio without mechanical contact.

Simplified community installation management

The following is available with the ASSISTANT programming tool:

- Database with all equipment, transmitters and proximity cards/tags provided in each installation.
- Possibility of assigning standby codes. Functional transmitters, cards and tags can be sold without having to visit the installation.
- Stolen or lost transmitters, cards and tags can be replaced by new, functional ones without having to visit the installation.
- Registrations via PIN, 1 4-digit code can be allocated to a receiver and all transmitters/proximity elements must have the same PIN to be programmed in the equipment. 2 PIN codes per transmitter is permitted. Also available with the PROGMAN portable programming tool.
- Possibility of personalising devices with the installer code.
- Configuration of equipment parameters such as forbidding the radio and manual programming of devices.

TRANSMITTERS



GOPRO MINI · GOPRO2 · GOPRO4 MUVPRO2 · MUVPRO4

- 868 MHz, 2 or 4-channel programmable transmitters.
- Nominal range: 100 m.
- Power supply: 1 x 3Vdc CR2032 type.
- Consumption: 12mA.
- Battery lasts for approximately 2 years.
- Light operating indicator for low battery and signal transmission.
- High security rolling code, 19 trillion combinations.
- Laser-marked series number.
- Operating temperature -20°C a $+55^{\circ}\text{C}$.
- Size of GOPRO MINI: 55 x 30 x 10 mm.
- Size of GOPRO: 62 x 33 x 11 mm.
- Size of MUVPRO: 68 x 36 x 14,4 mm.

RECEIVERS

Receivers MOTION.

BASE

WAVE

STICK

CONNECT

ACCESS500

ACCESS1000

and control panels with built-in receivers


TRANSMITTERS



ASSISTANT



PROGMAN



SOFTAssistant



GOPRO4

GOPRO2



MUVPRO2

MUVPRO4



GOPRO MINI

radio 868 MHz - 100 meters



ACCESS1000



WAVE500
ACCESS500



BASE



STICK